



LICENSE-FREE WALKIE TALKIES

Handfunkgerät

Transceptor

Talkie Walkie

AM845

Communicates with all other PMR 446 radio

Up to 10 km range

Provides extended signal range with 968 channel combinations.

Water proof

VOX

Voice-activated transmission frees hands for other tasks.

VibrAlert®

Enhanced vibrating feedback to notify you of incoming transmissions.

Built-in LED flashlight

Micro-USB cable, dock charger & rechargeable AA NiMH batteries included

May also be used with AA alkaline batteries.



Nothing Comes Close to a Cobra®

www.cobrapmr.com

Features

Benefits

UHF/FM	Ultra-clear long distance reception.
10 KM Range	Up to 10 KM range.(Range will vary depending on terrain and conditions.)
8 Channels	Front panel push buttons provide easy access to all 8 channels.
121 Privacy Codes	38 CTCSS (Continuous Tone Coded Squelch System) codes and 83 DCS (Digitally Coded Squelch) codes provide a total of 121 privacy codes. 968 privacy combinations are possible when the 8 channels are combined with the 121 privacy codes.
VOX (Voice Activated Transmission)	User's voice is detected and the radio transmits without the need to press any buttons, freeing the user's hands for other tasks. 5 VOX sensitivity levels allow user to select at which point the radio will detect their voice.
Water Proof	Helps to keep out moisture.
Rubberized Grips	For more assured handling.
Built-in LED Flashlight	Handy illumination located on the bottom of the radio cabinet.
Patented VibrAlert®	Enhanced vibrating feedback to notify you of incoming transmissions.
Scan	Allows user to scan either channels, CTCSS privacy codes within a channel, or DCS codes within a channel to locate conversations in progress.
10 Call tones	Provides up to 10 easily reconfigurable alert for incoming calls.
Roger Beep Tone (selectable on/off)	Confirmation tone indicates the completion of the user's transmission, and signals to others it is clear to talk. This feature is selectable and can be turned on or off.
Key Lock	When activated, provides key pad security eliminating accidental channel changes.
Power Saver	A unique circuit extends the life of your batteries. If there are no transmissions within 10 seconds, the unit will automatically switch to battery saver mode.
Auto Squelch	Automatically shuts off weak transmissions or unwanted noise due to terrain or range constraints.
LCD Display	Easy to view display provides the radio's status at a glance.
6 AA NiMH Rechargeable Batteries	Radios can also be used with 3 AA alkaline batteries per radio (not included).
Micro-USB charging cable	Charges supplied rechargeable batteries inside radios. Accommodates 1 or 2 radios.
Speaker/Microphone/Jack	Allows use of wall charger, or earphone speaker/microphones (not included) for "hands-free" operation.
Multilingual Manual	Includes a 8 language instruction manual.
Belt Clip	Secures your microTALK® radio while on the go.
No Licence or Service Fees	High quality band frequencies with no fees.

Unit Specifications - General

Unit Dimension	171mm x 65.77mm x 43.12mm (6.73" x 2.59" x 1.70")	SKU#	AM845	Master Package Dimension	213mm x 240mm x 290mm (8.38" x 9.44" x 11.40")
		UPC	8 56062 00625 8		
Unit Weight	130.5 g. (5.60 oz.) without batteries	RF Output	500 mW	Master Pack Weight	2470g. (87.16 oz.)
Channels	8 Channels CH1 = 446.00625 MH 2 = 446.01875 3 = 446.03125 4 = 446.04375 5 = 446.05625 6 = 446.06875 7 = 446.08125 8 = 446.09375	Master Pack Qty	4	*Specifications subject to change without notice* *All dimensions (H x W x L)*	
		Package Dimension	240mm x 195mm x 56mm (9.44" x 7.67" x 2.20")		
		Batteries	3 AA NiMH rechargeable batteries per radio (included) or can use 3 AA alkaline batteries per radio (not included)		

8 Language Manual Includes:



Cobra, microTALK, Nothing Comes Close to a Cobra, and the snake design are registered trademarks of Cobra Electronics Corporation, USA.

Cobra Electronics Corporation is a trademark of Cobra Electronics Corporation, USA.

©2016 Altis Global Limited, Berkeley Lake, GA 30071, USA



* Packaging is made from recyclable materials.

Nothing Comes Close to a Cobra®