



Compact mono laser printer

HL-1210W All in Box





brother.co.uk/hl-1210w-all-in-box

Compact wireless mono laser printer

Perfect for home or small offices with both wireless and mobile connectivity.

This affordable HL-1210W is fast and compact, offering excellent value for money.

HL-1210W All in Box





Key features:

- 5 x toners in the box, each printing 1,000 pages*
- Wireless and mobile connectivity
- 150 sheet paper input
- 20 pages per minute (ppm) print speed
- Compact size.

Everything you need for 3 years of printing* in one box

In the box with the HL-1210W, you will receive five high yield toners, which in total allows you to print 5,000 pages**. Not only that, this machine comes with a 3 year warranty as standard – so your printing needs will be covered for the next 3 years.

Compact and desktop friendly

Whether it's at home or in the office you can put the compact HL-1210W wherever it's most convenient for you.

Built with convenience in mind

Gone are the days of needing endless wires to connect to your printer. With the HL-1210W anyone around the home or office can connect quickly and easily via the wireless connection, or alternatively print direct from a mobile or tablet device; you don't even need to turn on a computer.



^{*}Bundle does not include paper

^{**}Print yield is based on 138 pages per month. Yield is declared in accordance with ISO/IEC 19752.

General

Technology

Electrophotographic laser

Processor

ARM9 200Mhz

Memory

32MB

Wireless network

IEEE 802.11b/g/n

Control panel

LED

Local interface

Hi-speed USB 2.0

Mobile print

Print from your mobile devices to your Brother printer

Warranty

3 year warranty

Print

Print speed (A4)

21ppm printing speed

Resolution

2,400 x 600dpi (HQ1200 technology)

First print out time

Less than 10 seconds from ready mode and standard tray

Warm up time

Less than 18 seconds from sleep mode

Print languages

GDI

Printer functions

N-up printing³

Reduce up to 2, 4, 9, 16 or 25 A4 pages into just one A4 page (Mac, up to 2, 4, 6, 9, or 16)

Manual 2-sided print4

Manual 2-sided printing (recommended for media not supported by automatic 2-sided print)

Poster printing⁴

Enlarge 1 A4 page into a poster using 4, 9, 16 or 25 A4 pages

Watermark printing4

Watermark your documents with predefined text or with your own user-defined messages

Printer driver

Windows

Windows XP Home and Professional, Vista, 7, 8, 8.1 Windows Server 2012, 2012R2, 2008, 2008 R2, 2003, 2003 x64 Edition

Macintosh⁵

OS X v10.7.5, 10.8.x, 10.9.x

Linux⁵

CUPS, LPD/LPRng (x86/x64 environment)

* Windows Server supports network printing only

¹ Approx declared vield value in accordance with ISO/IEC 19798.

² Calculated with 80g/m² paper.

³ Windows and Mac® only.

⁴ Windows only.

⁵ Optional download.

⁶ Maximum number of printed pages per month can be used to compare designed durability between like Brother products. For maximum printer life, it is best to choose a printer with a duty cycle that far exceeds your print requirements.

Paper handling

Paper input

Standard tray - 150 sheets

Paper output

50 sheets face down (80g/m2)

Media types and weights Standard tray

Plain and recycled paper (between 65 - 105g/m2)

Media sizes Manual feed slot

A4, letter, legal, folio, A5, A5 (long edge), B5, executive

Mobile and web connectivity

Brother iPrint&Scan (Android)

Print from, scan to, preview copies and check the machine status from an Android device

Brother iPrint&Scan (iPad / iPhone / iPod)

Print from, scan to, preview copies and check the machine status from an iPad/iPhone/ iPod Touch

Brother iPrint&Scan (Windows Phone)

Print from a smart phone running the Windows
Phone operating system

Brother iPrint&Scan (Windows 8,10 and RT)

Print from a Windows 8, 10 or Windows RT tablet

Brother print service plugin

Print from Android devices without a dedicated app

Fleet management tools

Unattended installer4

Ability to centrally deploy and customise our drivers and software

MSI installer4

Modular installers that can be distributed through active directory®

BRAdmin light^{4&5}

LAN/WAN management software

Embedded web server

Web based print management software embedded onto the device

Driver deployment wizard4

Easily create print drivers for hassle free deployment over your network

PrintSmart cost control

Monitor and control printing costs for all Brother and 3rd party devices.

For more information on PrintSmart solutions visit; brother.co.uk

Software

Brother iPrint&Scan (Windows & Mac)⁵

Print from and check the machine status from Windows, macOS or PC

¹ Approx declared yield value in accordance with ISO/IEC 19798.

² Calculated with 80g/m² paper.

³ Windows and Mac® only.

⁴ Windows only.

⁵ Optional download.

⁶ Maximum number of printed pages per month can be used to compare designed durability between like Brother products. For maximum printer life, it is best to choose a printer with a duty cycle that far exceeds your print requirements.

Network and security

Wireless network

IIEEE 802.11b/g/n (Infrastructure Mode/ Ad-hoc Mode)

Wireless network security

WEP 64/128, WPA-PSK (TKIP/ AES), WPA2-PSK (AES), SMTP-AUTH

Wireless setup support WPS, AOSS

Wireless applicationsVertical pairing

IPv4

ARP, RARP, BOOTP, DHCP, APIPA(Auto IP), WINS/NetBIOS name resolution, DNS resolver, mDNS, LLMNR responder, LPR/LPD, Custom Raw Port/ Port 9100, IPP, FTP Server, SNMPv1/v2c, HTTP Server, TFTP Client and Server, SMTP Client, ICMP, Web Services (Print)

IPv6

NDP, RA, DNS Resolver, mDNS, LLMNR responder, LPR/LPD, Custom Raw Port/ Port 9100, IPP, FTP Server, SN-MPv1/v2c, HTTP Server, TFTP Client and Server, SMTP Client, ICMPv6, Web Services (Print)

IP filter

Restrict which network users can or cannot access the device over the network (IPv4 only)

E-mail notifications

Automatically have the device send e-mail alerts when it requires attention, such as when the toner is low or needs replacing

Supplies and accessories

In-box toner¹ 5,000 pages black

(in accordance with ISO/IEC 19752)

Standard yield toner¹

5 x 1,000 pages black (in accordance with ISO/IEC 19752)

Drum unit1

10,000 pages (1 page/job) (DR-1050)

Dimensions and weights

With carton (WxDxH)

430 x 363 x 474 mm 8.1kg

Without carton (WxDxH)

340 x 238 x 189 mm 4.6kg

Duty cycles

Recommended monthly

250 to 1,800 pages monthly print volume

Maximum monthly6

Up to 10,000 pages monthly print volume

Environment

Power consumption

Printing - 380w Ready - 40w Deep sleep - 0.7w

TEC value 0.7 kWh/week

Sound pressure level

Printing - 51dB(A) Ready - Inaudible

Sound power

Printing - 6.6dB(A)
Ready - inaudible
Deep sleep - inaudible

¹ Approx declared yield value in accordance with ISO/IEC 19798.

² Calculated with 80g/m² paper.

³ Windows and Mac® only.

⁴ Windows only.

⁵ Optional download.

⁶ Maximum number of printed pages per month can be used to compare designed durability between like Brother products. For maximum printer life, it is best to choose a printer with a duty cycle that far exceeds your print requirements.





Working with you for a better environment

At Brother, our green initiative is simple. We strive to take responsibility, act respectfully and try to make a positive difference to help build a society where sustainable development can be achieved. We call this approach Brother Earth.

www.brotherearth.com

